



APC Replacement Battery Cartridge for Smart-UPS Line Interactive, 24V 9Ah lead-acid battery, 2-year repair or replace warranty

APCRBC124

Overview

Lead time Usually in Stock

Main

Product or component type	Replacement battery cartridge	
Battery type	Lead-acid battery	
Provided equipment	All required connectors Battery recycling guide Installation guide Reusable packaging	
Range of product	Replacement Battery Cartridges	

Batteries & Runtime

Number of battery free slots	0
Number of battery filled slots	0
Battery voltage	24 V
Number of battery replacement quantity	1

Physical

Height	76 mm
Width	152 mm
Depth	203 mm
Net weight	5.6 kg
Mounting mode	Not rack-mountable

Output

Battery capacity 9.0 Ah

Packing Units

Unit Type of Package 1	PCE
Number of Units in Package 1	1
Package 1 Height	27.500 cm
Package 1 Width	23.400 cm
Package 1 Length	14.600 cm

Package 1 Weight	5.828 kg
SCC14	10731304284380

Contractual warranty

Warranty (in months)

24



Schneider Electric aims to achieve Net Zero status by 2050 through supply chain partnerships, lower impact materials, and circularity via our ongoing "Use Better, Use Longer, Use Again" campaign to extend product lifetimes and recyclability.

Environmental Data explained >

How we assess product sustainability >

⊘ Environmental footprint		
Total lifecycle Carbon footprint	41	

Use Better

Packaging made with recycled cardboard	Yes
Packaging without single use plastic	No
EU RoHS Directive	Pro-active compliance (Product out of EU RoHS legal scope)
REACh Regulation	REACh Declaration
∜ Energy efficiency	
Energy Efficiency Optimized	Energy efficient product

Use Again

○ Repack and remanufacture		
End of life manual availability	End of Life Information	
Take-back	No	
WEEE Label	The product must be disposed on European Union markets following specific waste collection and never end up in rubbish bins	

Product datasheet

APCRBC124

Image of product / Alternate images

Alternative

