

Product datasheet

Specifications



APC Smart-UPS X Battery Pack Extension Cable 120V

SMX040

Overview

Presentation	Accessory solutions to tailor the Smart-UPS to meet your specific needs.
Lead time	Usually in Stock

Main

Product or component type	Cable
Battery type	VRLA
Provided equipment	Installation guide
Range of product	Smart-UPS Accessories

Batteries & Runtime

Number of battery free slots	0
Number of battery filled slots	0
Battery power in VAh	0 VAh

Physical

Colour	Black
Height	13 mm
Width	25 mm
Depth	1219 mm
Net weight	0.8 kg
Mounting mode	Not rack-mountable

Packing Units

Unit Type of Package 1	PCE
Number of Units in Package 1	1
Package 1 Height	12.7 cm
Package 1 Width	17.8 cm
Package 1 Length	24.8 cm
Package 1 Weight	910 g

Contractual warranty

Warranty (in months)	12
----------------------	----



Environmental Data

Schneider Electric aims to achieve Net Zero status by 2050 through supply chain partnerships, lower impact materials, and circularity via our ongoing “Use Better, Use Longer, Use Again” campaign to extend product lifetimes and recyclability.

[Environmental Data explained >](#)

[How we assess product sustainability >](#)

Environmental footprint

Total lifecycle Carbon footprint	4
----------------------------------	---

Use Better

Materials and Substances

Packaging made with recycled cardboard	No
--	----

Packaging without single use plastic	No
--------------------------------------	----

EU RoHS Directive	Compliant with Exemptions
-----------------------------------	---------------------------

SCIP Number	5ac12844-46eb-471b-94f1-318e06a714a6
-------------	--------------------------------------

REACH Regulation	REACH Declaration
------------------	-----------------------------------

Use Again

Repack and remanufacture

End of life manual availability	End of Life Information
---------------------------------	---

Take-back	No
-----------	----

WEEE Label	 The product must be disposed on European Union markets following specific waste collection and never end up in rubbish bins
------------	---